

## Copper Mechanical Connectors

Join two cables end-to-end.

### LOCKTITE® Two-Way Connectors


- Cables held by saddle and tightened by screws
- Built-in lockwashers
- For use with code copper conductor (600V)



CAT. NO.	CABLE SIZE	DIMENSIONS (IN.)		
		A	E	J
32503 <sup>1</sup>	14 Sol. to 8 Sol.	1½	¾	15/32
32505 <sup>1</sup>	8 Sol. to 4 Str.	1¾	½	17/32
32507	4 Sol. to 1 Str.	1¾	5/8	27/32
32509	1 Sol. to 2/0	1¾	¾	1½
32511	2/0 to 4/0	2¼	19/16	1¼
32513	4/0 to 300	2¼	1½	1½
32515	300 to 500	2¾	1¼	129/32
32517	500 to 750	3½	1½	2¼
32519	750 to 1,000	3¾	11/16	23/32

<sup>1</sup>With Filister Head Screw.

For torque requirements, see page F-188.



Designed for easy, one-person installation.

### LOCKTITE® Tee-Parallel Taps

- Tap hangs on main while branch is inserted
- Simply tighten screw to lock in place
- For use with code copper conductor (600V)



CAT. NO.	CABLE SIZE		DIMENSIONS (IN.)		
	MAIN	BRANCH	A	B	C
35011	300 to 500	2 to 3/0	2½	1¾	1¼
35013	300 to 500	4/0 to 500	3¼	1¾	1½
35015	500 to 750	2 to 3/0	23/16	119/16	1¼
35017	500 to 750	4/0 to 500	3¾	2¼	1¾
35019	500 to 750	500 to 750	4	2¼	2¼

For torque requirements, see page F-188.

