

General Duty Safety Switches

• Revised •
09/01/2015

Selection

1
SAFETY
SWITCHES



System	Ampere Rating	Indoor – Type 1		Horsepower Ratings ^①						
				240V AC						250 Volt DC
		Catalogue Number	Ship. Wt. (lbs.) Std. Pkg.	1-Phase, 2-Wire		2-Phase, 4-Wire		3-Phase, 3-Wire		
Std.	Max.			Std.	Max.	Std.	Max.			

240 Volt Fusible

2-Pole, 2-Fuse, and Solid Neutral^{②③}

240 Volt AC/250 Volt DC

Diagram	Ampere Rating	Catalogue Number	Ship. Wt. (lbs.) Std. Pkg.	1-Phase, 2-Wire Std.	1-Phase, 2-Wire Max.	2-Phase, 4-Wire Std.	2-Phase, 4-Wire Max.	3-Phase, 3-Wire Std.	3-Phase, 3-Wire Max.	250 Volt DC Std.
	30	GFC221N	35 ^④	1 1/2	3	—	—	3	7 1/2	5
	60	GFC222N	14	3	10	—	—	7 1/2	15	10
	100	GFC223N	23	7 1/2	15	—	—	15	30	20
	200	GFC224N	47	15	—	—	—	25	60	40

3-Pole, 3-Fuse, and Solid Neutral^④

240 Volt AC/250 Volt DC

Diagram	Ampere Rating	Catalogue Number	Ship. Wt. (lbs.) Std. Pkg.	1-Phase, 2-Wire Std.	1-Phase, 2-Wire Max.	2-Phase, 4-Wire Std.	2-Phase, 4-Wire Max.	3-Phase, 3-Wire Std.	3-Phase, 3-Wire Max.	250 Volt DC Std.
	30	GFC321N	24 ^④	1 1/2	3	—	—	3	7 1/2	5
	60	GFC322N	15	3	10	—	—	7 1/2	15	10
	100	GFC323N	25	7 1/2	15	—	—	15	30	20
	200	GFC324N	49	15	—	—	—	25	60	40

① Dual horsepower ratings: Std.- applies when non-time delay fuses are installed. Max.- applies when time-delay fuses are installed.
② Service entrance labeled.

③ Suitable for use on 3-phase motor loads.
④ 5 switches per standard package.
⑤ 10 switches per standard package.