







## 4 in. Octagonal Boxes

### Nonmetallic Sheathed Cable Clamps

		
<b>BC54151-L</b>	<b>BC54151-LB</b>	<b>BC54151-LD</b>
Prepositioned depth tabs recessed 1/2 in.	Side bracket, with holding prongs and prepositioned depth tabs.	Swing-arm" rework brackets. Max. wall thickness: 3/4 in.. Max. load capacity: 12 lb. (5.5 kg).
		
<b>BC54171-L</b>	<b>BC54171-LB</b>	<b>CI54171-LF</b>
Side bracket, with holding prongs.	Side bracket, with holding prongs.	Ceiling fan box. (Supplied with 2 #10-32 machine screws and star washers.) Max. load capacity: 35 lb. (15.6 kg).



Cat. No.	Volume (Cu. in.)	Features		Knockouts		Pryouts	
		Bracket	Raised Ground Screw	1/2 in. sides	1/2 in. bottom	sides	bottom
<b>1-1/2 in. Deep</b>							
<b>BC54151-L</b>	15.0	-	no	2	1	4	4
<b>BC54151-LB</b>	15.0	"B"	no	1	1	4	4
<b>BC54151-LD</b>	15.0	rework	-	-	1	4	4
<b>2-1/8 in. Deep</b>							
<b>BC54171-L</b>	21.0	-	-	2	1	4	4
<b>BC54171-LB</b>	21.0	"B"	-	1	1	4	4
<b>CI54171-LF</b>	21.0	-	no	2	1	4	4

FOR USE WITH NONMETALLIC SHEATHED CABLE ONLY

Note: CEC 2012 rule 30-302: Subrule (4) requires that a ceiling-mounted luminaire weighing 23 kg or less be supported on a ceiling outlet box attached directly to the building structure. A bar hanger may also be used to attach a ceiling outlet box to the building structure when the luminaire weighs 23 kg or less.