
# EVOLUTION<sup>™</sup> 8AT SERIES POKE-THRU DEVICE

**Evolution 8AT Series Poke-Thru Devices Ordering Information (continued)** 

#### **8STC** Recessed Assembly with Disposable Plate



NOTE: UL Fire Classified for up to 2 hour rated floors. Includes 8" diameter poke-thru stem assembly with a disposable plate. Devices are recessed 3 1/4" [83mm] below floor surface. No cover assembly is included. For use with the following cover assemblies (purchased separately): 8CTC and 8CT Series.

## 


For Side Compartments: • No Device Plates are provided

- For Center Compartments:
- No Device Plates are provided

#### For Bottom Feed Compartments:

- One (1) 5PTHA 1/2-Gang Pass-Through Housing Assembly
- Three (3) 1PTHA 1-Gang Pass-Through Housing Assembly
- One (1) 575CHA 1/2-gang 3/4"
- Conduit Housing Assembly\*\* • One (1) 8DIV 8" Divider
- NOTE: For more information on Device Plates and Bottom Feed Plates and on the additional options available, see the Device Plates and Bottom Feed Plates sections found later in this document.

8STCP Recessed Prewired Assembly with Disposable Plate



NOTE: UL Fire Classified for up to 2 hour rated floors.

NOTE: Receptacles can be wired as a standard or isolated ground device. Includes 8" diameter poke-thru stem assembly with a disposable plate. Devices are recessed 3 1/4" [83mm] below floor surface. No cover assembly is included. For use with the following cover assemblies (purchased separately): 8CTC and 8CT Series.


#### INCLUDED

- For Side Compartments:
- Two (2) proprietary 20 Amp Duplex Receptacles installed
- No Device Plates are provided
- For Center Compartments:
- No Device Plates are provided

#### For Bottom Feed Compartments:

- One (1) 5BLH 1/2-Gang Blank Housing\*
  Three (3) 1PTHA - 1-Gang
- Pass-Through Housing Assembly
- One (1) 575CHA 1/2-gang 3/4" Conduit Housing Assembly\*\*
- One (1) 8DIV 8" Divider
- \* Tunneling extends from the 5BLH to 575CHA so that power cables from the 20A duplex receptacle mounted on the left side of the poke-thru device are run into the junction box attached to the 575CHA.
- \*\* Also includes junction box attached to the 3/4" conduit.

#### 8PPS 8" Pre-Pour Poke-Thru Sleeve




Nonmetallic sleeve attaches to structural decking and plywood decking designs while maintaining a 8"-8 1/8" diameter cast in hole. Unit includes three (3) attachment legs, two (2) end caps and three (3) thumb screws.



NOTE: Pre-Pour Sleeves for 6" (6PPS) and 8" (8PPS) Evolution Series Poke-Thru Devices speed installation and insure accurate location of devices.

### ABPLUG8 Abandonment Plug



Complete abandonment plug assembly for 8" diameter hole. Assembly comes complete with intumescent material to maintain a 2-hour fire classification of the floor.